D7212GV2 Control Panel

www.boschsecurity.com

BOSCH
Invented for life

- Fully integrated intrusion and fire functions allow users to interface with one system instead of two
- Conettix IP based communication option provides high-speed, secure alarm transport and control
- Four programmable areas with perimeter and interior partitioning
- 40 points with flexible configuration options to meet application specific requirements
- Your choice of vacuum fluorescent or ATM style user interface command centers

The D7212GV2 Control Panel provides an integrated solution for intrusion (commercial and residential) and residential fire alarm system applications. Monitor alarm points for intruder or fire alarms while operating user command centers and other outputs. The D7212GV2 Control Panel includes a communicator that sends event reports to selected public switched telephone network (PSTN) or IP network destinations through four programmable route groups. Program all system functions on-site through a D5200 Programmer or remotely through Remote Programming Software (RPS).
The D7212GV2 Control Panel provides up to 40 individually identified points. Each point accommodates normally-open and normally-closed devices with end-of-line (EOL) resistor supervision. Each point is programmable for fire, fire supervisory, or intrusion applications.

Notice
The D7212GV2 Control Panel is available exclusively to Bosch Certified Security Dealers (BCSD).

Functions

Programmable Outputs
- 2 A alarm power at 12 VDC
- 1.4 A auxiliary power at 12 VDC
- Four alarm output patterns
- Automatic bell test
- Programmable bell shut-off timer
- Three on-board outputs, 24 off-board programmable outputs

System Response
- 31 custom point indexes, including fire supervisory
- Selectable point response time
- Cross point capability
- Fire alarm verification
- Watch mode
- Scheduled events (skeds) arm, disarm, bypass and unbypass points, control relays, and control authority levels

Area Configurations
Area programming offers a wide selection of different system configurations. Each area is assigned an account number to define annunciation, control, and reporting functions. Multiple areas can be linked to a shared area which is automatically controlled (hallway or lobby). Area arming can be conditional on other areas (master or associate).

User Interface

- Supervises up to eight command centers (up to 32 non-supervised command centers can be used)
- Custom command center text
- Four custom functions
- Full function command menu including custom functions
- Each user has authority by area and 16-character name
- 14 custom authority levels control user's authority to change, add, delete passcodes, delete access control tokens, delete cards, disarm, bypass points, and initiate system tests
- Up to 40 programmable, scheduled events and up to 16 event functions for controlling relays, enabling passcodes and windows, and automatically arming and disarming areas
- Adjustable brightness or volume for command center display or sounder
- One parallel printer

The D7212GV2 provides on-premises point and system status annunciation. The fully selectable user interface customizes command center displays and allows users to create appropriate menu items and functions. Function lists can help a user become familiar with the operation of the control panel and custom functions allow users to perform complex functions with a few keystrokes. Each function can be programmed and identified by sixteen characters of custom text and can contain up to 32 keystrokes.

Notice

At least one command center per system is recommended.

Two Man Rule

Two Man Rule requires two unique passcodes on the same command center to disarm an area. Without the second passcode, the system denies entry. Two Man Rule requires the presence of two people at opening, providing added security.

Early Ambush

Early Ambush requires two passcode entries on the same command center. Enter the same passcode twice or have two unique passcodes, depending on the configuration. The first entry disarms the area and the second entry stops a timer programmed to send a duress event. If the second entry does not occur within the programmed time, the system generates a duress event. Early Ambush allows users to inspect the premises and use the system to confirm that the area is safe to enter, providing added security.

Easy Exit Control

The D7212GV2 Control Panel changes from one armed state to another armed state without disarming. For example, if you change the state from Master Arm to Perimeter Arm, the control panel complies and reports the change. Easy Exit Control reduces the number of keystrokes, simplifying system operation.

Programmable Passcode-controlled Menu List

The system prompts users to enter a passcode prior to viewing the command center menu. The command center display shows the user the menu options allowed according to the user's authority level. Passcode-controlled menus provide users only with the options and information pertinent to them, simplifying system operation.

Passcode Follows Scope

Use Passcode Follows Scope to restrict passcode arming and disarming only to the command center's immediate local area, even if the command center can report events from other areas. Passcode follows scope simplifies the arming and disarming procedure without limiting any other command center command capabilities.

Passcodes

User passcodes contain three to six digits. Assign each user one of 14 customized authority levels in each area. Restrict passcodes to operate only during certain times.

The Two Man Rule and Early Ambush options require two passcodes, providing additional security in financial establishments such as banks.

Communications

The D7212GV2 prioritizes and sends reports to four route groups. Each group has a programmable primary and backup destination.

The D7212GV2 works with the D6600 NetCom Communications System using a DX4020 Network Interface Module. It has programmable anti-replay anti-substitution features when using a DX4020.

The Modem IIIa^2 Communications Format, available with Bosch receivers, adds reporting capabilities such as:

- Individual point numbers and text
- Opening or closing reports by area number
- Remote programming attempts
- Diagnostic reports

Security and Fire Detection

The D7212GV2 Control Panel provides eight on-board points, and up to 32 additional off-board points (depending on model and expansion interfaces). You can program individual points to monitor all types of burglar alarms, fire alarms, and supervision devices.

Event Log

The event log stores up to 1,000 local and transmitted events. The event log includes time, date, event, area, point, and user number. View the event log from select command centers or remotely retrieve event information using RPS. RPS operators can retrieve events periodically using one phone call, rather than receiving several calls each day. When the event log reaches a programmed threshold of stored events, it can send an optional report to a receiver.

Scheduled Events (Skeds)

The internal clock and calendar start individually scheduled events (skeds). Skeds perform functions such as arm or disarm, relay control, or point bypassing. The D7212GV2 Control Panel offers:

- 40 scheduled events with up to 16 different functions available
- Eight opening windows and eight closing windows
- Eight user windows
- Day-of-week, date-of-month, or holiday only schedules
- Four holiday schedules of 366 days each (leap year)

Fire Test

When a user activates Fire Test Mode, the control panel suppresses all reports to the central station. The command center and annunciator show all testing data. An automatic sensor reset feature saves time; you do not need to reset the sensors manually. At the end of test, the command center shows the number of untested points.

Programming, Diagnostics and Controls

Users can program on-site with a D5200 Programmer, or program remotely through RPS. A programmable system passcode prevents unauthorized remote programming.

D7212GV2 Control Panels accommodate up to four separate telephone numbers for primary, alternate, and backup receivers for automatic test reports. When resetting alarms or arming or disarming a system, the user is identified by name and number.

Certifications and approvals

Region	Certification	
USA	UL	AMCX: Central Station Alarm Units (UL1610, UL1635), AMCX7: Central Station Alarm Units Certified for Canada (CAN/ULC-S304-M88, UL 1635), AMTB: Control Panels, SIA False Alarm Reduction (ANSI/SIA CP-01-2000), AOTX: Local Alarm Units (UL464, UL609), AOTX7: Local Alarm Units Certified for Canada (CAN/ULC-S303, CAN/ULC-S525), APAW: Police Station Alarm Units (UL365, UL464), APAW7: Police Station Alarm Units Certified for Canada (CAN/ULC -S303, CAN/ULC-S304, CAN/ULC-S525), APOU: Proprietary Alarm Units (UL1076), APOU7: Proprietary Alarm Units Certified for Canada (ULC/ORD-C1076), NBSX: Household Burglar Alarm System Units (UL1023), NBSX7: Household Burglar Alarm System Units Certified for Canada (ULC/ORD-C1023), UTOU: Control Units and Accessories - Household System Type (UL985), UTOU7: Control Units and Accessories - Household System Type Certified for Canada (ULC-S545)
	CSFM	7167-1615:0100 CONTROL UNIT (HOUSEHOLD)
	FCC	AJ9-MUL-46532-AL-E
Canada	IC	1249A-GV2

Installation/configuration notes

Compatible Products

Keypads	D1260 Series Keypads (D1260, D1260W, D1260R, D1260BLK, D1260B)
	D720 Series Keypads (D720, D720W, D720R, D720B)
	D1255 Series Keypads (D1255, D1255W, D1255R, D1255B)
	D1256 and D1256RB Fire Keypads
	D1257 and D1257RB Remote Fire Alarm Annunciator
	D279A Independent Zone Control
Detectors	D278S Four-wire Addressable Detector Base
	D285/TH Photoelectric Smoke Detector Heads
	D298S Addressable Detector Base
	D7050 Series Addressable Photoelectric Smoke and Smoke Heat Detector Heads
	F220-B6PM/S Addressable Detector Bases with POPITs
	MX250 Series Smoke Detectors
	MX775i Addressable PIR Detector
	MX794i Long Range Multiplex PIR Detector
	MX934i Addressable PIR Detector
	MX938i Addressable PIR Detector
	ZX776Z PIR Detector
	ZX794Z Long Range PIR Detector
	ZX835 TriTech Microwave/PIR Detector
	ZX935Z PIR Detector
	ZX938Z PIR Detector
	ZX970 PIR/Microwave Detector
	Bosch conventional detectors, including Blue Line, seismic, PIR, TriTech PIR Microwave, photoelectric, heat, and smoke.
Enclosures	D8103 Universal Enclosure
	D8108A Attack-Resistant Enclosure
	D8109 Fire Enclosure
Magnetic Contacts	Bosch magnetic contacts include recessed, terminal connection, miniature, overhead door, and surface mount.
Modules	C900V2 Dialer Capture Module
	D113 Battery Lead Supervision Module
	D125B Dual Class B Initiating Module

	D127 Reversing Relay Module
	D129 Class A Initiating Module
	D130 Auxiliary Relay Module
	D185 Reverse Polarity Signaling Module
	D192C Notification Appliance Circuit Module
	D192G Notification Appliance Circuit Module
	D928 Phone Line Switcher
	D5060 MUX Programmer
	D8125 POPEX Point Expander
	D8128D OctoPOPIT Eight Point Expander
	D8125MUX Point Expander
	D8125INV Wireless Interface Module
	D8129 Octo-relay Module
	D8130 Door Release Module
	D9127 Series POPIT Modules
	D9131A Parallel Printer Interface Module
	DS7432 Eight-input Remote Module
	DS7457i Series Single Zone Multiplex Input Modules
	DS7460i Two-input Module
	DS7461i Single-input Multiplex Module
	DS7465i Input and Output Module
	DX4010i RS-232 Serial Interface Module
	DX4020 Network Interface Module
Peripheral Hardware	rvm4c Remote Video Module
Communications	Modem IIIa[2]
Formats	BFSK
Programming	D5200 Series Programmers
	Remote Programming Software (RPS)
SAFECOM Radio	SC2104 Series Slave Communicators
Communicators	SC3100 Series Data Transfer Radio Communicators
	SC4000 Series Full Data Transfer Radio Communicator
Commercial	ISW-D8125CW Commercial Wireless Interface
Wireless Products	ISW-EN7280 Serial Receiver
	ISW-EN4200 Serial Receiver
	ISW-EN4204R LED Receiver
	ISW-EN4216R LCD Receiver
	ISW-EN4016SK Survey Receiver
	ISW-EN5040-T High-power Repeater
	ISW-EN1210 Universal Transmitter (Single-input)
	ISW-EN1210EOL Universal Transmitter with EOL Resistor
	ISW-EN1210SK Survey Transmitter
	ISW-EN1210W Door-Window Transmitter with Reed Switch
	ISW-EN1215EOL Universal Transmitter with Wall Tamper and EOL Resistor
	ISW-EN1215WEOL Door-Window Transmitter with Wall Tamper, Reed Switch, and EOL Resistor
	ISW-EN1223D Water-resistant Pendant Transmitter (Double-button)
	ISW-EN1223S Water-resistant Pendant Transmitter (Single-button)
	ISW-EN1223SK Survey Pendant Transmitter
	ISW-EN1233D Necklace Pendant Transmitter (Double-button)
	ISW-EN1233S Necklace Pendant Transmitter (Single-button)
	ISW-EN1235D Beltclip Pendant Transmitter (Double-button)
	ISW-EN1235S Beltclip Pendant Transmitter (Single-button)
	ISW-EN1235DF Fixed-location Transmitter (Double-button)
	ISW-EN1235SF Fixed-location Transmitter (Double-button)
	ISW-EN1242 Smoke Detector-Transmitter
	ISW-EN1247 Glass-break Sensor Transmitter
	ISW-EN1249 Billtrap Transmitter
	ISW-EN1260 PIR Motion Sensor Transmitter (Commercial and High-end Domestic Applications)
	ISW-EN1261HT PIR Motion Sensor Transmitter (High-traffic Areas)
	ISW-EN1262 PIR Motion Sensor Transmitter (Residential and Low-traffic Commercial Applications)
	ISW-EN1265 PIR Motion Sensor Transmitter (Ceiling-mount Applications)

Parts included

D7212GV2 Components	Quantity
D7212GV2 Board	1

Mounting Skirt	1
Faceplate with D7212GV2 Label	1

Technical specifications

Communications

SDI Bus A (+):	9 VDC 4572 m (15,000 ft)
SDI Bus B (-):	9 VDC 4572 m (15,000 ft)
Telephone Connection:	RJ31X or RJ38X

Environmental Considerations

Relative Humidity:	5% to 85% at +30°C (+86°F), non-condensing
Temperature (Operating):	0°C to +50°C (+32°F to +120°F)

Number of...

Areas:	4
Custom Functions:	4
Programmable Relay Outputs:	27
Events:	Store up to 1,000
Parallel Printers:	1
Passcode Users:	99, plus 1 service passcode
Points:	40 (eight on-board, up to 32 off-board)
RF Points:	32
SKEDs:	40

Power Requirements

Current Draw (Minimum):	200 mA
Current Draw (Maximum):	500 mA
Output (Alarm):	2 A at 12 VDC
Output (Auxiliary, Continuous Power, and Switched Auxiliary combined):	1.4 A at 10.2 VDC to 13.9 VDC
Voltage (Operating):	12 VDC
Voltage (AC):	16.5 VAC 40 VA plug-in transformer (D1640)
Voltage (DC):	• Up to 2 12 VDC, 7 Ah sealed lead acid rechargeable batteries • Up to 2 12 VDC, 18 Ah sealed lead acid rechargeable batteries

The D7212GV2 Control Panel is available exclusively to Bosch Certified Security Dealers (BCSD).

D7212GV2 Kit Ordering Information

	Kits				
Components	**D7212GV2K1**	**D7212GV2-CA-K1**	**D7212GV2K1W**	**D7212GV2K2**	**D7212GV2-CA-K2**
D7212GV2 Board	1		1	1	
D7212GV2-CA Board		1			1
D101 Lock and Key Set	1	1	1	1	1
D1255 Keypad	1	1			
D1255W Keypad (White)			1		
D1260 Keypad				1	1
D1640 Transformer	1		1	1	
D1640-CA Transformer		1			1
D8103 Enclosure	1	1	1	1	1
DS835i PIR Detector	2	2	2	2	2

	Kits				
Components	**D7212GV2K3**	**D7212GV2-CA-K3**	**D7212GV2K3W**	**D7212GV2K4**	**D7212GV2-CA-K4**
D7212GV2 Board	1		1	1	1
D7212GV2-CA Board		1			
D101 Lock and Key Set	1	1	1	1	1
D1255 Keypad	1	1			
D1255W Keypad (White)			1		
D1260 Keypad				1	1
D1640 Transformer	1	1	1	1	1
D1640-CA Transformer					
D8103 Enclosure	1	1	1	1	1
D8125 Addressable Expansion Module	1	1	1	1	1
D9127U POPIT Module without Tamper	10	10	10	10	10

	Kits					
Components	**D7212GV2K5**	**D7212GV2-CA-K5**	**D7212GV2K5W**	**D7212GV2K6**	**D7212GV2K7**	**D7212GV2K8**
D7212GV2 Board	1		1	1	1	1
D7212GV2-CA Board		1				
D101 Lock and Key Set	1	1	1	1	1	1
D1255 Keypad	1	1			1	
D1255W Keypad (White)			1			
D1260 Keypad				1		1
D1640 Transformer	1		1	1	1	1
D1640-CA Transformer		1				
D8103 Enclosure	1	1	1	1	1	1
DS835i PIR Detector					1	1
D8128D OctoPOPIT Eight-Point Expander					1	1
DX4020 Network Interface Module	1	1	1	1		

Ordering information

D7212GV2 Kit with Keypad and PIR Detectors (2) for Canada
Contains one PCB, one lock and key set, one transformer, one universal enclosure, two PIR detectors, and one D1260 Keypad.
Order number **D7212GV2-CA-K2**

D7212GV2 Kit with Keypad and POPIT Modules (10) for Canada
For use in Canada. Contains one PCB, one lock and key set, one transformer, one universal enclosure, one expansion module, ten POPIT modules, and one D1255 Keypad.
Order number **D7212GV2-CA-K3**

D7212GV2 Kit with Keypad and POPIT Modules (10) for Canada
For use in Canada. Contains one PCB, one lock and key set, one transformer, one universal enclosure, one expansion module, ten POPIT modules, and one D1260 Keypad.
Order number **D7212GV2-CA-K4**

D7212GV2 Kit with Keypad and Network Interface Module
Contains one PCB, one lock and key set, one transformer, one universal enclosure, one D1255 Keypad, and one DX4020 Network Interface Module.
Order number **D7212GV2K5**

Accessories

ICP-EZTS Dual Tamper Switch
Combination tamper switch with a wire loop for additional tamper outputs.
Order number **ICP-EZTS**

D101 Lock and Key Set
Short-body lock set with one key supplied. Uses the D102 (#1358) replacement key.
Order number **D101**

D122 Dual Battery Harness
Harness with circuit breaker. Connects two batteries to a compatible control panel.
Order number **D122**

D122L Dual Battery Harness with Long Leads
Color-coded harness with circuit breaker and leads measuring 89 cm (35 in.). Connects 12 V batteries to compatible control panels.
Order number **D122L**

D126 Standby Battery (12 V, 7 Ah)
A rechargeable sealed lead-acid power supply used as a secondary power supply or in auxiliary or ancillary functions.
Order number **D126**

D137 Mounting Bracket
Used to mount accessory modules in D8103, D8108A, and D8109 enclosures.
Order number **D137**

D138 Mounting Bracket, Right Angle
Used to mount accessory modules in D8103, D8108A, and D8109 enclosures.
Order number **D138**

D1218 Battery (12 V, 18 Ah)
A 12 V sealed lead-acid battery for standby and auxiliary power with two bolt-fastened terminals. Includes hardware for attaching battery leads or spade connectors
Order number **D1218**

D1224 Battery (12 V, 26-28 Ah)
A 12 V sealed lead-acid battery for standby and auxiliary power with two bolt-fastened terminals. Includes hardware for attaching battery leads or spade connectors.
Order number **D1224**

D1238 Battery (12 V, 38 Ah)
A 12 V sealed lead-acid battery for standby and auxiliary power with two bolt-fastened terminals. Includes hardware for attaching battery leads or spade connectors.
Order number **D1238**

D1640 Transformer
System transformer rated at 16.5 VAC, 40 VA.
Order number **D1640**

D1640-CA Transformer
For use in Canada. System transformer rated at 16.5 VAC, 40 VA.
Order number **D1640-CA**

D8103 Enclosure
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.).
Order number **D8103**

D8108A Attack Resistant Enclosure
Grey steel enclosure measuring 41 cm x 41 cm x 9 cm (16 in. x 16 in. x 3.5 in.). UL Listed. Includes lock and key set. Requires the D2402 Mounting Plate.
Order number **D8108A**

D9002-5 Mounting Skirt
Mounts inside D8103, D8108A, and D8109 enclosures. Can accept up to six standard 7.62 cm x 12.7 cm (3 in. x 5 in.) cards.
Order number **D9002-5**

D136 Plug-In Relay
Maximum rating is 1 A at 24 VDC or 2 A at 12 VDC. Available individually (D136) or in a package of 25 (D136-25).
Order number **D136**

Software Options

RPS Kit (LPT)
Account management and control panel-programming software with LPT connection.
Order number **D5500C-LPT**

RPS Kit (USB)
Account management and control panel programming software with USB security key (dongle).
Order number **D5500C-USB**

Represented by:

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:
Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:
Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com

© Bosch Security Systems 2013 | Data subject to change without notice
2494115723 | en, V1, 01. Oct 2013